

Yealink T42G Setup Guide

To configure the Yealink T42G to your Montec Group account, first retrieve the IP Address so that you can log into the 'Web Configuration' via your computer. To do this, the 'OK' button in the middle of the D-Pad. The IP Address should show up in the Status Page. Enter The IP Address into your web browser.

Once you are on the Web Configuration page enter the username and password. By default the username will be 'admin' and the Password will be 'admin'.

Once you have successfully logged in, click on the 'Account' tab across the top. Here you will place your Extension information and the SIP Server (***sip.monconnect.com.au*** for Residential and Sip Trunk accounts, and ***pbx.monconnect.com.au*** for Hosted PBX accounts) as the bellow screenshot shows:

The screenshot shows the 'Account' configuration page for 'Account 1'. The 'Advanced' tab is selected in the left sidebar. The main configuration area is divided into sections for 'SIP Server 1' and 'SIP Server 2'. The 'SIP Server 1' section is highlighted with green boxes around the following fields: 'Line Active' (Enabled), 'Label' (Optional), 'Display Name' (Optional), 'Register Name' (Extension Number), 'User Name' (Extension Number), 'Password' (Extension Password), 'Outbound Proxy Server' (pbx.monconnect.com.au), 'Transport' (UDP), 'Server Host' (pbx.monconnect.com.au), and 'Server Expires' (120). The 'SIP Server 2' section has 'Server Expires' (3600) highlighted. A 'NOTE' panel on the right provides definitions for 'Display Name', 'Register Name', 'User Name', and 'NAT Traversal'. At the bottom, there are 'Confirm' and 'Cancel' buttons.

Field	Value	Port
Register Status	Registered	
Line Active	Enabled	
Label	Optional	
Display Name	Optional	
Register Name	Extension Number	
User Name	Extension Number	
Password	Extension Password	
Enable Outbound Proxy Server	Enabled	
Outbound Proxy Server	pbx.monconnect.com.au	5060
Transport	UDP	
NAT	Disabled	
STUN Server		3478
SIP Server 1		
Server Host	pbx.monconnect.com.au	5060
Server Expires	120	
Server Retry Counts	3	
SIP Server 2		
Server Host		5060
Server Expires	3600	
Server Retry Counts	3	

Hit the 'Confirm' Button at the bottom of the page to save the details. Once the page has reloaded, click on advanced and type '50002' into the 'Voicemail' field. This is the voicemail number. Again hit 'Confirm' to save the settings.

Next, click on the 'DSSKey' tab at the top. In here you will configure the multiple lines for the once extension, allowing you to make and receive multiple calls through your extension number.

Key	Type	Value	Label	Line	Extension
Line Key1	Line	Default		Line 1	
Line Key2	Line	Default		Line 1	
Line Key3	Line	Default		Line 1	
Line Key4	Line	Default		Line 1	
Line Key5	Line	Default		Line 1	
Line Key6	Speed Dial			Line 1	
Line Key7	Speed Dial			Line 1	
Line Key8	Speed Dial			Line 1	
Line Key9	Speed Dial			Line 1	

NOTE

Key Type
The free function key 'Types' Speed Dial, Key Event, Intercom.

Key Event
Key events are predefined shortcuts to phone and call functions.

Intercom
Enable the 'Intercom' mode and it is useful in an office environment as a quick access to connect to the operator or the secretary.

Copyright © 1998-2012 **Inc. All Rights Reserved

Feel free to also setup some Speed Dials for important numbers. If you would like to setup BLF (Busy Lamp Field) to see the status of the other extensions please refer to the *BLF Guide* for this phone model on the Montec Group website.

Now that the lines have been configured, you will now want to set the time zone and time format, which can be done under the top 'Settings' tab, and then the 'Time and Date' button on the left.

At this point, the phone should be ready to go. If you have any troubles making and receiving calls from here on in, please give Montec Group a call on **1300 011 585**.