

Gigaset C610IP Setup Guide

The first step is to plug your base station into power and network. Now press the button and the IP address will appear on the screen of the handset. Once you have the IP address, type it into your internet browser. The Default pin is 0000

Click on the Settings tab, and then click on Telephony. Now click Edit for "IP1". Enter your extension information (found in your Montec Connect portal) into these fields like bellow:

The screenshot shows the Gigaset web interface with the 'Settings' tab selected. The left sidebar contains a menu with 'Telephony' highlighted. The main content area is titled '1, IP Connection' and includes the following fields and buttons:

- Connection Name or Number:** A text input field containing 'Optional'.
- Auto Configuration:** A section with a text input field for 'Auto Configuration Code' and a 'Start Auto Configuration' button.
- Provider:** A dropdown menu set to 'Other Provider' with a 'Select VoIP Provider' button.
- Personal Provider Data:** A section with four text input fields: 'Authentication Name' (containing 'Extension Number'), 'Authentication password' (containing 'Extension Password'), 'Username' (containing 'Extension Number'), and 'Display name' (containing 'Extension Number').
- Buttons:** A 'Show Advanced Settings' button and three buttons at the bottom: 'Set', 'Cancel', and 'Delete'.

Click on Show Advanced Settings. Type the Domain address in and change the Registration Refresh time to 120 Seconds and click Set and you are done.

The screenshot displays the 'Advanced Settings' window for a SIP provider configuration. The window is titled 'Hide Advanced Settings' at the top. It is divided into two main sections: 'General Provider Data' and 'Network'.

General Provider Data:

- Domain:
- Proxy server address:
- Proxy server port:
- Registrar server:
- Registrar server port:
- Registration refresh time: sec

Network:

- STUN enabled: Yes No
- STUN server:
- STUN port:
- STUN refresh time: sec
- NAT refresh time: sec
- Outbound proxy mode: Always Auto Never
- Outbound proxy:
- Outbound proxy port:

At the bottom of the window, there are three buttons: 'Set', 'Cancel', and 'Delete'. The 'Set' button is highlighted with a green border.

SIEMENS

Keep in mind that if you are a SIP customer you will use "sip.monconnect.com.au" as the Sip Server.

