

## X-Lite Softphone Setup Guide

To configure X-Lite to your Montec Connect account, first download and install the program. Run the application and Click 'Softphone' then choose 'Account Settings'

Here you will place your Extension information and the SIP Server (*sip.monconnect.com.au* for Residential and Sip Trunk accounts, and *pbx.monconnect.com.au* for Hosted PBX accounts) as the bellow screenshot shows:

The screenshot shows the 'SIP Account' configuration window in X-Lite. The 'Account' tab is active. The 'Account name' field contains 'Optional'. The 'Protocol' is set to 'SIP'. Under 'Allow this account for', both 'Call' and 'IM / Presence' are checked. In the 'User Details' section, the 'User ID' is 'Extension Number', the 'Domain' is 'pbx.monconnect.com.au', the 'Password' is 'Extension Password', the 'Display name' is 'Optional', and the 'Authorization name' is 'Extension Number'. In the 'Domain Proxy' section, 'Register with domain and receive calls' is checked, and 'Send outbound via' is set to 'Domain'. The 'Dial plan' is '#1\a\a.T;match=1;prestrip=2;'. The 'OK' and 'Cancel' buttons are at the bottom right.

Now click on the 'Advanced' tab at the top right. Change the "Register Every" to 120 Seconds. Now Click 'OK' at the bottom.

The screenshot shows the 'SIP Account' configuration window with the 'Advanced' tab selected. The 'Register Settings' section is visible. The 'Reregister every' field is set to '120' seconds. The 'Minimum time' is set to '20' seconds and the 'Maximum time' is set to '1800' seconds. The 'Advanced' tab is highlighted with a green box.